

## VISTA-20P

### CONTROL PANEL



The high capacity, feature-rich VISTA-20P lets you deliver more value to your customers on each and every sale with up to 48 zones of protection, Internet uploading/downloading, graphic keypad support and dual partitions. VISTA-20P gives you the ability to send alarm signals and upload/download via an Internet Protocol (IP), improving the speed at which information can be delivered to and from the control panel. In addition, the VISTA-20P, used with an AlarmNet Internet or digital communicator can be installed in premises without TELCO lines with no sacrifice in functionality. The panel's installation advantages, innovative end-user benefits and robust system capacity make the value-priced VISTA-20P an ideal choice for higher end installations.

## FEATURES

- IP alarm reporting and uploading/downloading capability for Internet and Intranet use via iGSMV, 7845i-ENT or GSMV
  - Supports four graphic touchscreen keypads
  - Wireless keys can be programmed without using zones
  - Eight on-board hardwired zones standard (15 when Zone Doubling feature is used)
    - 40 hardwire expansion zones
    - 40 wireless expansion zones
  - Two low current on-board trigger outputs
  - 100 Event Log viewable at system keypads with time/date stamp
  - 48 system user codes assignable to either partition
  - Expandable to 48 total zones when used with hardwired and/or wireless expansion modules
  - Two independent partitions plus a common partition
    - Global Arming from any system keypad
    - Go to function to view or operate one partition from the other
    - Separate partition account numbers
  - 16 output devices
    - Relays (Model 4204 Relay Modules, or 4229 Expansion Module), and/or X-10® devices (when used with a 4300 Transformer)
  - Four installer-configurable zone types allows the installer to create custom zone types by assigning all zone attributes
  - Supports four-wire and up to 16 two-wire smokes
    - Works with Sentrol CleanMe™ maintenance signal
  - Multiple actions on output devices depending on system state
    - Turns lights off when system arms
    - Turns the same light on when system disarms
    - Flashes same lights when system is in alarm
  - Built-in phone line cut monitor with programmable delay and annunciation options
    - Display on system keypads
    - Trigger local sounders
    - Trigger system bell
  - Dynamic Signaling
    - Reduces redundant reporting to the central station when multiple reporting methods are used; i.e. digital dialer and AlarmNet radio
- ### Valuable End-User Features
- Viewable on system keypads:
    - Exit countdown
    - Time and date display\*
    - Event log\*
  - Auto keypad backlighting on entry
  - Keyswitch arming
  - Programmable macro buttons and single-button arming
  - Supports a variety of wireless remote controls for single-button operation
  - User Scheduling
    - Automatically activates X-10 and relays at programmed times
    - Latchkey reports to pagers
    - Auto arm/disarm
    - "User access" time windows
  - Supports up to four end-user numeric pagers
  - VIP Module allows system control from any touchtone phone
  - Chime by zoneo
- \*Requires custom alpha keypad
- ### Security Dealer Features
- Automatic System Load Shed
    - During extended AC power fail, the system battery will be disconnected to prevent irreversible battery failure. Reduces service calls to replace batteries.

# VISTA-20P

## CONTROL PANEL

### SPECIFICATIONS

#### Electrical

- Aux. power 12VDC, 600mA maximum
- Seven hour standby at 400mA aux. load with four amp hour battery
- 16.5VAC/25VA transformer
- Alarm output 12VDC, 2.0 amps max.
  - For UL installations, combined aux. and alarm output cannot exceed 700mA

#### Output Control

- Supports up to four relay boards (up to 16 relays)
- Optional X-10 transformer/interface (part no. 4300) may be used to control up to 16 X-10 receiving devices

#### Zones

- Eight hardwired zones (15 with zone doubling)
- Selectable response 10msec, 350msec, 750msec
- Assignable to any partition
- 20 selectable zone types plus four configurable zone types
- Programmable swinger suppression

#### Expansion Devices

- 4219 – Eight hardwired zones – 16mA
- 4204 – Up to four relays – 15mA standby (each active relay draws an additional 40mA)
- 4229 – Eight hardwired zones and two relays – 36mA (each active relay draws an additional 40mA)

#### Accessories

- iGSMV Internet and Digital Cellular Communicator with Remote Service Capability
- 7845i-ENT Enterprise Internet Communicator
- GSMV Digital Cellular Communicator with Remote Service Capability
- 4286 VIP Voice Module – 220mA
- 5881ENL RF Receiver supports up to eight zones – 60mA
- 5881ENM supports up to 16 zones – 50mA
- 5881ENH supports up to 48 zones – 50mA
- 5883 Transceiver supports up to 40 zones – 80mA

#### Keypads

- 6160 Custom Alpha (required for programming) – 100mA
- 6160V Custom Alpha Voice – 100mA
- 6150 Fixed English LCD – 85mA/40mA
- 6150V Fixed English Voice LCD – 85mA/40mA
- 6150RF Fixed English RF LCD – 85mA/40mA
- 6148 Fixed English LCD – 70mA/30mA
- 6270 Graphic Touchscreen
- 6272CBV Graphic Touchscreen with Voice (Black)

- 6272CSV Color Graphic Touchscreen with Voice (Silver)
- 6272CV Color Graphic Touchscreen with Voice (White)
- 8132 Advanced User Interface

#### Agency Listings

- ETL Residential Fire, Burglary and Commercial Burglary

#### Smoke Detectors

- Supports up to 16 two-wire smoke detectors
- Supports four-wire smoke detectors

#### Communications

- iGSMV Internet and Digital Cellular Communicator with Remote Service Capability
- 7845i-ENT Enterprise Internet Communicator
- GSMV Digital Cellular Communicator with Remote Service Capability
- Touchtone or pulse
- Formats supported
  - ADEMCO Contact ID
  - ADEMCO 4 + 2 Express
  - ADEMCO low speed
  - Sescoc/Radionics
- 3 + 1, 4 + 1 and 4 + 2 reporting
- Reporting capabilities
  - Split
  - Dual
  - Split/Dual – True dial tone detection
- Low battery reports 11.2 – 11.6VDC
- AC loss and restoral reporting supported

## ORDERING

<b>VISTA-20P</b>	Control Panel
<b>VISTA-20PSIA</b>	Control Panel for CP-01 SIA Certifications

#### For more information:

[www.honeywell.com/security/hsc](http://www.honeywell.com/security/hsc)

#### Automation and Control Solutions

Honeywell Security & Communications  
2 Corporate Center Dr. Suite 100  
P.O. Box 9040  
Melville, NY 11747  
1.800.467.5875  
[www.honeywell.com](http://www.honeywell.com)

L/VISTA20PD/D  
June 2011  
© 2011 Honeywell International Inc.

# Honeywell