

JFS-381

(Fault Stand-By AMP Switcher)



>FEATURES

Stand-By amplifier will be turn on automatically incase main amplifier is out of order on the way of operatating to announce emergency situation or important broadcasting.

LED indicator will be flashed and buzzer will make sound.

AC/DC 24V

>SPECIFICATIONS

Technical	
Capacity	8 Main Amplifiers 1 Stand-by Amplifier
Audio input / AMP INPUT	1 : 1
AMP output / SPK LINE	1 : 1
Frequency response	Less than-0.5dB (20Hz~20kHz)
Signal to Noise ratio	More than 86dB
T.H.D	Less than 0.005%
Cross-talk	More than 80dB
Power Consumption	12W
GENERAL	
Power(option)	120V/230V/240VAC 50/60Hz , 24VDC
Dimensions(mm)	483(W) x 133(H) x 350(D)
(inch)	19(W) x 5.2(H) x 13.8(D)
Weight(kg/lbs)	7.0 / 15.4