

VC-05R / VC-05RF



MODEL	VC-05R	VC-05RF
Type	5 - step resistive, mono	
Power Rating	6 watts	
24 VDC Override	No	Yes
Attenuation	Step 1: OFF Step 2: - 4 dB Step 3: - 1 dB Step 4: - 0.5 dB Step 5: 0 dB	
Frequency Response	20 Hz - 20 kHz	
Dimensions	86 (W) x 86 (H) x 50 (D) mm (VC - 305 R) 115 (W) x 70 (H) x 48 (D) mm	

VC-30W / VC-30WF



MODEL	VC-30W	VC-30WF
Type	5 - step auto transformer, mono	
Power Rating	30 watts	
24VDC Override	No	Yes
Attenuation	Step 1: OFF Step 2: - 17 dB Step 3: - 11 dB Step 4: - 4.5 dB Step 5: 0 dB	
Frequency Response	20 Hz - 20 kHz	
Dimensions	86 (W) x 86 (H) x 62 (D) mm (VC - 3030W) 115 (W) x 70 (H) x 64 (D) mm	

VC-60W / VC-60WF



MODEL	VC-60W	VC-60WF
Type	5 - step auto transformer, mono	
Power Rating	60 watts	
24VDC Override	No	Yes
Attenuation	Step 1: OFF Step 2: - 18 dB Step 3: - 11 dB Step 4: - 5 dB Step 5: 0 dB	
Frequency Response	20 Hz - 20 kHz	
Dimensions	86 (W) x 86 (H) x 70 (D) mm (VC - 3060 W) 115 (W) x 70 (H) x 74 (D) mm	

VC-120W / VC-120WF



MODEL	VC-120W	VC-120WF
Type	5 - step auto transformer, mono	
Power Rating	120 watts	
24VDC Override	No	Yes
Attenuation	Step 1: OFF Step 2: - 17 dB Step 3: - 11 dB Step 4: - 5.5 dB Step 5: 0 dB	
Frequency Response	20 Hz - 20 kHz	
Dimensions	86 (W) x 86 (H) x 50 (D) mm	
Transformer Dimensions	70 (W) x 70 (H) x 28 (D) mm (VC - 3120 W) 115 (W) x 70 (H) x 74 (D) mm	