



FRONT PANEL



REAR PANEL

KB-D13B

16-ZONE SPEAKER SELECTOR

Easy operation with all on/all off buttons and Clear indication of zone state with different color indication.

FEATURES

- 16 monitor channels, independent volume for each monitor channel
- LCD display current monitor channel and the correspondent monitor volume
- Select monitor channel and control monitor volume through buttons
- 7 grades (0-6) volume control for each channel
- Automatic cycle monitor function, set cycle time through remote control unit
- Have functions of remotely read the present monitor channel and volume, remote turning on/off, remote monitor channel selection, remote volume control, remote cycle monitor control and remote time-set of automatic cycle monitor
- Short circuit signal activation
- Apply switch of address setting, use decimal system to set the local address

SPECIFICATIONS

Input	70 / 100 V audio signal
Output	Output maximum for each zone:150w
Priority bus	16channels activated by 0V signal
Power handling	1.5KW total capacity
Alarm Out	0 V signal
Power Requirements	AC 220V ± 10% 50-60Hz
Power Consumption	20~30W
Dimensions	89(H) × 483(W) × 350(D)mm
Weight	5.4Kg
Material	6.6Kg

Ordering Information

KB-D13B 16-Zone Speaker Selector

KB-D13B