

Audio Sources

KB-C240PV

This high quality 2-zone mixer amplifier offers 240Wrms and features dual EQ controls allowing adjustment of the bass and treble frequencies, suitable for powering medium to large sound systems where music may be required in one area and quiet in the rest of the building.

- 2 output channels, one for music or speech ,the other for speech only
- Master volume, Bass and Treble control, individual knob for level adjustment of each input
- Vox priority Mic1and Mic2; Inputs 3,4,5 can be switchable between microphones and line inputs
- 4 pin phoenix connector for both balanced mic or tell in
- Booster output offered connection to additional amplifier system when more power is needed
- Three balanced combo jack inputs; RCA jack line inputs
- Operation on AC power or 24V DC
- Brackets are provided for 19in rack ins tallation



Specifications	KB-C240PV
Mic Inputs	0.8mV / 600ohm
Aux Inputs	100mV, 500mV, 1V
Signal/Noise ratio, Mics	>60dB
Signal/Noise ratio, Aux	>70dB
Frequency Response	50Hz-18kHz
THD	<1% at rated power
Bass Control	+/- 10dB at 100Hz
Treble Control	+/- 10dB at 10kHz
Power Output RMS	240W
AC Power Supply	110V/60Hz or 230V/50Hz
DC Power	24V
Booster Output	1V / 600ohm
Dimensions	88(H) x 428(W) x 268(D) mm
Weight	10.2kg