

AM/FM DIGITAL R.D.S TUNER

## TP-100RDSU



### FEATURES

- Hi-blend function
- Digital electronic tuner
- RDS(Radio Data System) function
- Manual, seek up/down tuning
- 24Station preset memory(FM:18, AM:6)
- AF, CT, PI, PS, PTY function

### ACCESSORY



### SPECIFICATIONS

|                       |                                                 |
|-----------------------|-------------------------------------------------|
| TUNING RANGE          | FM 87.5~108Mhz/AM 522~1620KHz                   |
| ANT IMPEDANCE         | FM AM Common<br>300Ω balanced or 75Ω unbalanced |
| USABLE SENSITIVITY    | FM : 2dBμV / AM : 4.5dBμV                       |
| SIGNAL TO NOISE RATIO | FM : More than 60dB / AM : More than 50dB       |
| T.H.D                 | FM : Less than 0.2% / AM : Less than 0.5%       |
| SEEK STOP SENS        | FM : 25dB / MW : 30dB                           |
| DIMENSIONS (mm)       | 194(W) x 40(H) x 80(D)                          |
| WGIGHT (kg)           | 0.5kg                                           |